

HomeAware™ Beacon

RF Transmitter for ReliAlert™ and ReliAlert™ XC

SecureAlert's HomeAware™ Beacon is a Radio Frequency (RF) transmitter that compliments the ReliAlert™ XC and ReliAlert™ GPS devices, providing agencies with



added RF home detention capability. The Beacon is a completely self-contained, short-range transmitting station that provides a secure, continuous RF signal. GPS tracking is provided until the offender enters communication range of the Beacon; at which point, RF tracking begins.

RF Tracking in conjunction with GPS monitoring increases the ability to maintain critical offender location information and provides agencies with an effective way to more accurately “tether” an offender to a specific location.

Self-Contained Technology offers agencies greater flexibility for use in a variety of locations because no landline or external power source is required.

Multiple-Use Options allow agencies to customize Beacon usage based upon the tracking needs required for individuals or groups of individuals. Multiple Beacons can be utilized for one offender (home, counseling, etc.) or one Beacon can be installed for the presence tracking of multiple offenders at a specific location (halfway house, group home, etc).

Call 1.866.451.6141 or visit www.securealert.com for more information

SECUREALERT
Reliability. Peace of Mind.

Reset People Selected Offenders Time Last 6 Hours Place All Places

6AM 7AM 8AM 9AM 10AM 11AM 12PM 1PM 2PM 3PM 4PM 5PM

Map Satellite Hybrid Ruler 50 ft 20 m

Shelbrooke Dr Shelbrooke Dr S 1375 W S 1330 W Wood Stone Cir

Add Beacon

Beacon Name * Doe Residence

Address 1 * 1335 Wood Stone Cir. **Go**

Address 2

City * Salt Lake City

Country * USA

State/Province * Utah Postal Code 84108

Beacons at this location:

Name	ID

Name Doe Residence ID 841523 **Add Beacon**

OK Cancel

HomeAware™ Beacon Specifications

- ▲ **Beacon Signal:** transmitted every 20 seconds
- ▲ **Communication:** the ReliAlert™/ReliAlert™XC device monitors transmissions from assigned Beacon(s), then communicates Beacon status and alarms to the Monitoring Center
- ▲ **Power Source:** internal batteries provide one (1) year of operation
- ▲ **Multiple Battery Alarms:** a “low battery” alarm is generated when approximately 10-14 days of operation remain; a “battery critical” alarm is generated when approximately 3-5 days of operation remain
- ▲ **Tamper Detection:** motion sensors detect and alarm if the Beacon is moved after arming
- ▲ **Curfew Monitoring:** customizable schedules can be created for alarming when curfew parameters are not met
- ▲ **Multiple-Use:** one (1) Beacon can be utilized for unlimited offenders or multiple Beacons can be utilized for one (1) offender
- ▲ **Weight:** 7.8 oz (221g)
- ▲ **Dimensions:** 2.75" x 4.0" x 1.5" (7.0 x 10.2 x 3.8 cm)

Call 1.866.451.6141 or visit www.securealert.com for more information

SECUREALERT
Reliability. Peace of Mind.